

Hyundai HY1000Si 1kw Digital Inverter Generator:



The new Hyundai HY1000Si is the ideal generator for running moth traps, it is lightweight, quiet and good value for money, a very popular choice.

Features:

Low oil and Overload shutdown
 12v output for battery charging, 12v leads and clips
 Low Noise
 Lightweight

Specifications:

Model		HY1000Si
GENERATOR	Type	Digital Inverter/Sine Wave
	Rated AC Output (KW)	0.95
	Max AC Output (KW)	1.0
	Frequency (Hz)	50Hz
	Voltage (v)	230v
	Power Factor $\cos \phi$	1.0
ENGINE	Model	142F
	Type	Over head Valve/Forced-Air Cooling/single Cylinder/4 stroke Petrol engine
	Bore x Stroke	41.8mmX36mm
	Displacement ml	49CC
	Rated Power kw	1.2
	Max Power kw	1.4
	Ignition Mode	T.D.I
	Recommended Fuel	Unleaded Petrol
	Fuel Tank Capacity L	2.7
	Fuel Consumption h	420g/kw.h
	Engine Oil Capacity L	0.25
	Starting System	Pull start
	Continuous Work Time (hours)	6-9
Noise Level (7m)	58db (with no load)	
STANDARD FEATURES	Power Indicator Light	Yes
	AC Overload Protector	Yes
	AC Socket	Yes
	DC Socket (12v/8.3A)	Yes
DIMENSIONS	DC Protector	Yes
	Low Oil light	Yes
	Dimension mm	490mm x 275mm x 415mm
	Net weight kg	13.7